

Now available from www.M2Cshop.com

PhoneGuardian 110 Telephone

Big button, +40 dB Boost amplified receiver phone and Speakerphone with Emergency remote control, Large display and Talking Caller ID.

Following on from the success of the PhoneGuardian 100 care phone we have listened to our customers who wanted us to include a waterproof wrist pendant, and an even louder receiver. The result is the all new PhoneGuardian 110.



Features:

- Big button keypad
- 2-way speaker phone with LED indicator
- Amplified receiver, +40dB max with tone control (with LED indicator)

Now available from www.M2Cshop.com

- High Loudness ringer 90 dBA (at one foot)
- 3 Emergency dial memories M1, M2, and M3 (Emergency dialling activated by the remote control or pressing the M1, M2, M3 key)
- 30 phone book memories (non-volatile storage)
- 64 caller ID memories (Time / Day of call, 14 digits number, 16 characters name, non-volatile storage)
- Ringer LED indicator
- Large 3 line LCD display with backlight,
 - -1st row: 7 segment for new call, date/time, repeat / battery / Caller ID / phone book icon
 - -2nd row: 14 digits x 7 segments
 - -3rd row: 16 digits dot matrix
- New call indicator, flashing LED and LCD icon
- Last number redial
- Recall (100ms or 300ms)
- Clock (24 hour display)
- Caller ID memory call back
- Contrast control
- Up / Down review
- Store
- Pause
- Desktop or wall mountable
- Ringer volume control (High / Low / Off)
- Hearing Aid Compatible (ETS300381 preferred range)
- Receiver volume control (Rotary)

- Full waterproof IP57 emergency remote control (868 MHz, Factory preset code)
- Remote speakerphone answer on & off function
- Talking caller ID (Name & number, user recordable names)
- Factory pre-recorded voice prompts (0-9, Caller ID, Phone book, Default OGM)
- Menu system for phone setup

Controls:

- **Numeric digits 0 ~ 9, *, #**
- **Redial / Pause key**
- **Recall key**
- **M1 / M2 / M3, one touch emergency dial key**
- **Phone book / Caller ID key**
- **Hook Switch**
- **Speakerphone key (With LED indicator)**
- **Call back key**
- **Delete key**
- **Caller ID and Phonebook review key, up & down**
- **Speakerphone volume control (Slide)**
- **Booster on / off key**
- **Tone control (Slide) Menu Key**
- **Microphone mute key (press & hold)**
- **Remote control wristband unit: One key control with LED indicator**

Miscellaneous:

- **AC adaptor 9 volts DC @ 200mA**
- **Battery 6 volts (4xAA) in base unit for operation during power failure**
- **Full waterproof wristband remote control (Battery, 12 volts (A23) included)**
- **Fully modular 7ft UK line cord**
- **Fully modular 9ft coiled handset cord**